

ZONDA LED EMERGENCY 12W/1.2W, ceiling light with motion sensor, 800lm/80lm, IP20, 4000K, milky PC, white

Adviti

 Marka: **ADVITI** | Symbol: **AD-PL-391WLPMR4** | Ean: **5908254817601**


PRODUCT DESCRIPTION

This ceiling light is designed to automatically illuminate rooms such as: staircases, corridors, basements, garages, warehouses, etc. This lighting fixture has a meatly built-in PIR motion sensor, which is placed inside and, depending on the settings, it will detect even the smallest movement. Thanks to the two potentiometers, the sensor can be set according to the needs so as to operate exactly when people are present and moving in a given area. The settings include: lighting time in the range from 10 seconds to 12 minutes and light intensity. The maximum range of motion detection is 6m. The luminaire uses SMD LED diodes, which guarantee

high energy efficiency and have a long service life. The presented lamp works with rated power of 12 W and emits light with luminous flux of 800 lm. It shines with a natural white color at a temperature of 4000K. This indoor lamp also has an additional 3-hour emergency lighting function that switches on in the event of a power failure. This lighting is powered by a separate LED circuit (6 LEDs with a total power of 1.2W). The source of the emergency power supply is a built-in 3.7V lithium battery with a capacity of 1500mAh. The base of the lamp is made of a metal alloy, and the lampshade is made of unbreakable polycarbonate with a milky color.

TECHNICAL DATA

General information:

Luminous flux:	800 lm
Rated power:	12 W
Light source:	LED SMD
Degree of protection (IP):	20
Colour temperature:	4000
Nominal voltage:	230V~, 50Hz
Colour:	white
Dimensions - depth:	67 mm
Dimensions - width:	290 mm
Dimensions - height:	290 mm
Other features:	additional emergency lighting 1.2W (DC), 80lm
Colour rendering index CRI:	>85
Detection angle:	360°
Material of the lampshade:	polycarbonate
Control of the motion sensor:	Yes
Type of sensor:	PIR
Detection range:	6m m
Adjustable daylight sensor (LUX):	Yes
Daylight sensor adjustment range (LUX):	<3–2000lux
Adjustable time setting (TIME):	Yes
Lighting time adjustment range (TIME):	min: 10 sek. ± 3 sek.; max: 3 min. ± 30 sek.

Adjustment of motion detection range (SENS):

No



