

Lamp bulb socket with PIR motion sensor, 360°, IP20, E27 holder, 1x60W

VIRONEMarka: **Virone** | Symbol: **MS-2** | Ean: **5908254816994**

PRODUCT DESCRIPTION

The socket is used for automatic lighting control. Its task is to turn on and off the light source installed in the socket. No installation is required. Possible adjustment: time setting after motion detection and daylight sensor.

TECHNICAL DATA

General information:

| | |
|--|---|
| Max. load: | 60 W |
| Max. load of the LED light source: | 15 W |
| Degree of protection (IP): | 20 |
| Relay output: | No |
| Presence detector: | No |
| Working temperature: | -20~+40 |
| Daylight sensor adjustment range (LUX): | <3–2000lux |
| Adjustable daylight sensor (LUX): | Yes |
| Installation: | bulb socket |
| Detection range: | Ø6 m |
| Dimensions of the sensor - width (mm): | Ø50 mm |
| Dimensions of the sensor - height (mm): | Ø50 mm |
| Dimensions of the sensor - depth (mm): | 130 mm |
| Colour: | white |
| Nominal voltage: | 230V~, 50Hz |
| Detection angle: | 360° |
| Type of sensor: | Infrared |
| Lighting time adjustment range (TIME): | min: 10 sek. ± 3 sek.; max: 5 min. ± 1 min. |
| Adjustment of motion detection range (SENS): | No |
| Adjustable time setting (TIME): | Yes |

