

## Wireless radio frequency (RF) controller for RGBW strips (multi-coloured and white LED lighting strips) with white remote control

**ViRONE**

Marka: **Virone** | Symbol: **LH-8/6** | Ean: **5904988901159**



### PRODUCT DESCRIPTION

A reliable LED driver which controls the light colours of RGBW tape or RGBW LED modules. RF (radio) technology enables control from behind the wall (it is not an infrared remote control). Selected functions: ring of colours, flash effects, smooth, strobe, smooth transitions, smooth dimming and brightening and many others. The white remote control in a minimalist, modern design allows for easy, intuitive operation.

## TECHNICAL DATA

## General information:

|                               |                           |
|-------------------------------|---------------------------|
| Operating voltage:            | DC 12-24V                 |
| Max. load:                    | 3A (per channel)          |
| Output current:               | 18A for 12V / 36A for 24V |
| Output power:                 | 144W/288W                 |
| Control:                      | remote control            |
| Type of remote control:       | RF (radio waves)          |
| Controller width:             | 86 mm                     |
| Controller height:            | 45 mm                     |
| Controller depth:             | 23 mm                     |
| Width of remote control:      | 110 mm                    |
| Height of the remote control: | 52 mm                     |
| Depth of remote control:      | 23 mm                     |