

## Wireless radio frequency (RF) controller for RGB strips (multi-coloured LED lighting sets)

**ViRONE**

Marka: **Virone** | Symbol: **LH-8/2** | Ean: **5904988901111**



### PRODUCT DESCRIPTION

A reliable LED driver, which controls the light colours of RGB tape or RGB LED modules. Thanks to the "Power Off Memory" function, the driver remembers the settings during a power failure. RF (radio) technology enables control from behind the wall (it is not an infrared remote control). Selected functions: setting any colour of light, regulation of light brightness, 6 modes of automatic change: flashing colour change, automatic switching of subsequent modes, fluent change of seven colours, fluent change of three colours, jump change of seven colours, jump change of three colours.

## TECHNICAL DATA

### General information:

Operating voltage:	DC 12-24V
Output current:	8A
Output power:	96W for 12V / 192W for 24V
Control:	remote control
Type of remote control:	RF (radio waves)
Controller width:	131 mm
Controller height:	64 mm
Controller depth:	23 mm
Width of remote control:	85 mm
Height of the remote control:	52 mm
Depth of remote control:	7 mm







