

## PIR sound & motion sensor 160°

Marka: Orno | Symbol: OR-CR-206 | Ean: 5908235905235




### PRODUCT DESCRIPTION

Passive infrared sensor Operates in the two-wire system For indoor usage Regulation: lighting time (TIME), the sensitivity of the light intensity (LUX) and range of motion detection (SENS) Can be installed in the junction box of [średnica]60 mm.

## TECHNICAL DATA

### General information:

Max. load:	40-500
Degree of protection (IP):	20
Relay output:	No
Nominal voltage:	230V~, 50Hz
Presence detector:	No
Colour:	white
Installation:	flush mounting
Dimensions of the sensor - width (mm):	75 mm
Dimensions of the sensor - height (mm):	75 mm
Dimensions of the sensor - depth (mm):	45 mm
Working temperature:	-20~+40
Detection angle:	160°
Dimensions of the mounting hole:	Ø60 mm
Type of sensor:	Infrared
Detection range:	4-9m m
Adjustable daylight sensor (LUX):	Yes
Daylight sensor adjustment range (LUX):	<3-2000lux
Adjustable time setting (TIME):	Yes
Lighting time adjustment range (TIME):	min: 10 sek. ± 3 sek.; max: 7 min. ± 2 min.
Adjustment of motion detection range (SENS):	No



