

## Lamp bulb socket with PIR motion sensor

Marka: **Orno** | Symbol: **OR-CR-210** | Ean: **5901752480308**

**ORNO**


### PRODUCT DESCRIPTION

It controls any connected electrical device using a passive infrared sensor For indoor usage It works with ordinary light bulbs, LED and fluorescent lights Regulation: lighting time (TIME), the sensitivity of the light intensity (LUX) No need of installation.

## TECHNICAL DATA

### General information:

Max. load:	1x60W
Max. load of the LED light source:	15 W
Degree of protection (IP):	20
Relay output:	No
Nominal voltage:	230V~, 50Hz
Presence detector:	No
Colour:	white
Installation:	bulb socket
Dimensions of the sensor - width (mm):	Ø50 mm
Dimensions of the sensor - height (mm):	Ø50 mm
Dimensions of the sensor - depth (mm):	130 mm
Working temperature:	-20~+40
Detection angle:	360°
Type of sensor:	infrared
Detection range:	Ø6 m
Adjustable daylight sensor (LUX):	Yes
Daylight sensor adjustment range (LUX):	<3—2000lux
Adjustable time setting (TIME):	Yes
Lighting time adjustment range (TIME):	min: 10 sek. ± 3 sek.; max: 5 min. ± 1 min.
Adjustment of motion detection range (SENS):	No

