

## MINI motion sensor 360°

Marka: Orno | Symbol: OR-CR-263 | Ean: 5900378654773

**ORNO**



### PRODUCT DESCRIPTION

This small motion sensor is used to automatically control lighting or other electric appliances. The device is equipped with potentiometers to adjust lighting time and light intensity. It is compatible with LED diodes.

## TECHNICAL DATA

### General information:

Max. load:	400
Max. load of the LED light source:	100 W
Degree of protection (IP):	20
Relay output:	Yes
Nominal voltage:	230V~, 50Hz
Presence detector:	No
Colour:	white
Installation:	surface mounting
Dimensions of the sensor - width (mm):	Ø76 mm
Dimensions of the sensor - height (mm):	Ø76 mm
Dimensions of the sensor - depth (mm):	20.2 mm
Detection angle:	360°
Type of sensor:	Infrared
Detection range:	Ø8m m
Adjustable daylight sensor (LUX):	Yes
Daylight sensor adjustment range (LUX):	<3–2000lux
Adjustable time setting (TIME):	Yes
Lighting time adjustment range (TIME):	min: 10 sek. ± 3 sek.; max: 7 min. ± 2 min.
Adjustment of motion detection range (SENS):	No

