

Socket motion detector, 120°

Marka: Orno | Symbol: OR-CR-266 | Ean: 5908254806209

ORNO

PRODUCT DESCRIPTION

An electrical device designed to automatically switch on and off other electrical devices whenever motion is detected by a PIR sensor. The sensor is activated at an appropriate light intensity.

TECHNICAL DATA

General information:

Max. load:	1200 W
Max. load of the LED light source:	300W W
Degree of protection (IP):	20
Relay output:	Yes
Nominal voltage:	230V~, 50Hz
Presence detector:	No
Colour:	white
Installation:	network socket
Dimensions of the sensor - width (mm):	45 mm
Dimensions of the sensor - height (mm):	98.3 mm
Dimensions of the sensor - depth (mm):	81.5 mm
Working temperature:	-20~+40
Detection angle:	120°
Type of sensor:	Socket motion detector
Detection range:	9 m
Adjustable daylight sensor (LUX):	Yes
Daylight sensor adjustment range (LUX):	<3—2000lux
Adjustable time setting (TIME):	Yes
Lighting time adjustment range (TIME):	min.: 10 sek. ± 3 sek., max.: 15min,±2min
Adjustment of motion detection range (SENS):	Yes



