

Symmetric electric strike with unclosed door signalling, MINI, low current coil



Marka: **ORNO Home** | Symbol: **OR-EZ-4029** | Ean: **5908254804045**



PRODUCT DESCRIPTION

The smallest electric strike available on the market. It can work with the doorphones, video doorphones installation and code locks in the front of single- and multi-family doors. It can be mounted on the outside of the standard faceplate. Symmetrical design and small dimensions. Made of corrosion-resistant materials (aluminum and zinc alloy). Equipped with: safe, patented and adjustable latch keeper mechanism (2 mm). Electric strike has been equipped with Low current coil with wide voltage range, current consumption is 280mA for 12V direct current and 250mA for 12V alternating current.

TECHNICAL DATA

General information:

Power consumption during operation:	280mA / 12VDC
Direction of opening:	right/left
MINI size:	yes
Latch adjustment:	Yes
Nominal voltage:	9-24V AC/DC
Door open indicator:	Yes
Latch guide:	No
Mechanical unlocking:	No
Dimensions - depth:	16 mm
Dimensions - width:	28,1 mm
Dimensions - height:	72.7 mm
Other features:	door-open indicator
Memory:	No



