

## BULLED S floodlight 30W with PIR sensor

Marka: Orno | Symbol: OR-NL-6137BLR4 | Ean: 5900378659907




### PRODUCT DESCRIPTION

This floodlight is designed to provide lighting in houses and indoor areas, such as halls, garages. It is also suitable for outdoor use as lighting for parking areas, gardens, building, fences and billboards, etc. Built-in LED SMD diodes constitute the source of light. The device has also got a built-in PIR sensor which activates the light only when a motion is detected and allows adjustment of light activation time accordingly to user's preferences. The maximal detection range is 8 meters and light activation time can be set from 10 +/- seconds to 10 +/- minutes.

## TECHNICAL DATA

### General information:

Luminous flux:	2400 lm
Rated power:	30 W
Light source:	LED SMD
Degree of protection (IP):	44
Colour temperature:	4000
Nominal voltage:	230V~, 50Hz
Colour:	black
Solar panel:	No
Dimensions - depth:	75 mm
Dimensions - width:	155 mm
Dimensions - height:	158 mm
Colour rendering index CRI:	>80
Detection angle:	120°
Control of the motion sensor:	Yes
Type of sensor:	PIR
Detection range:	4-8 m
Adjustable daylight sensor (LUX):	Yes
Daylight sensor adjustment range (LUX):	<10 LUX~2000
Adjustable time setting (TIME):	Yes
Lighting time adjustment range (TIME):	10S±3S~10Min±3
Adjustment of motion detection range (SENS):	Yes



