







## SPINEL LED garden luminaire 10W with PIR motion sensor

Marka: Orno | Symbol: OR-OP-6119WLPMR4 | Ean: 5900378654803

ORNO



## PRODUCT DESCRIPTION

This garden luminaire features both, good quality and high durability. It can be mounted on building facades or concrete fences creating a unique lighting scene. Modern LED diodes guarantee high energy efficiency and long service lifetime. It is equipped with PIR sensor which triggers the lighting only when a motion has been detected, and a twilight sensor (depending on the settings) which switches the light on only when it is needed. The device has got potentiometers to adjust lighting time and light intensity. Made of shatterproof polycarbonate (PC).







## **TECHNICAL DATA**

## General information:

| Luminous flux:                               | 800 lm                                      |
|--|---|
| Rated power:                                 | 10 W  |
| Light source:                                | LED SMD                                     |
| Degree of protection (IP):                   | 54  |
| Colour temperature:                          | 4000  |
| Nominal voltage:                             | 230V~, 50Hz                                 |
| Colour:                                      | white                                       |
| Solar panel:                                 | No  |
| Dimensions - depth:                          | 90 mm                                       |
| Dimensions - width:                          | 289 mm                                      |
| Dimensions - height:                         | 147 mm                                      |
| Colour rendering index CRI:                  | >85   |
| Detection angle:                             | 140°  |
| Material of the lampshade:                   | polycarbonate                               |
| Control of the motion sensor:                | Yes   |
| Type of sensor:                              | PIR   |
| Detection range:                             | 9 m   |
| Adjustable daylight sensor (LUX):            | Yes   |
| Daylight sensor adjustment range (LUX):      | <3-2000lux                                  |
| Adjustable time setting (TIME):              | Yes   |
| Lighting time adjustment range (TIME):       | min: 10 sek. ± 3 sek.; max: 5 min. ± 1 min. |
| Adjustment of motion detection range (SENS): | No  |





























