

LED lighting fixture ZONDA emergency with PIR sensor, 16W

ORNO

Marka: Orno | Symbol: OR-PL-391WLPMR4 | Ean: 5901752486720



PRODUCT DESCRIPTION

Use of the LED technology guarantees high energy efficiency and long life of the ceiling light fitting. The lamp fits in with any interior due to its ultra-thin base with high quality non-breakable milk PC lampshade. The centrally located PIR motion detector responds to motion and the twilight sensor switches lighting on only if necessary (depending on settings). Equipped with a 3-hour emergency lighting function that activates in the event of a power supply failure.

TECHNICAL DATA

General information:

| | |
|--|---|
| Luminous flux: | 800 lm |
| Rated power: | 12 W |
| Light source: | LED SMD |
| Degree of protection (IP): | 20 |
| Colour temperature: | 4000 |
| Nominal voltage: | 230V~, 50Hz |
| Colour: | white |
| Dimensions - depth: | 67 mm |
| Dimensions - width: | 290 mm |
| Dimensions - height: | 290 mm |
| Other features: | additional emergency lighting 1.2W (DC), 80lm |
| Colour rendering index CRI: | >85 |
| Detection angle: | 360° |
| Material of the lampshade: | polycarbonate |
| Control of the motion sensor: | Yes |
| Type of sensor: | PIR |
| Detection range: | 6m m |
| Adjustable daylight sensor (LUX): | Yes |
| Daylight sensor adjustment range (LUX): | <3–2000lux |
| Adjustable time setting (TIME): | Yes |
| Lighting time adjustment range (TIME): | min: 10 sek. ± 3 sek.; max: 3 min. ± 30 sek. |
| Adjustment of motion detection range (SENS): | No |



