







## LED lighting fixture ZONDA with PIR sensor, 16W

Marka: Orno | Symbol: OR-PL-6076WLPMR4 | Ean: 5902560325782

ORNO



## PRODUCT DESCRIPTION

Use of the LED technology guarantees high energy efficiency and long life of the ceiling light fitting The lamp fits any interior due to its ultra-thin base with high quality non-breakable milk PC lampshade Centrally located PIR motion detector responds to motion and the twilight sensor switches the lighting on only if necessary (depending on settings).









## **TECHNICAL DATA**

## General information:

| Luminous flux:                               | 1100 lm                                      |
|--|--|
| Rated power:                                 | 16 W   |
| Light source:                                | LED SMD                                      |
| Degree of protection (IP):                   | 20   |
| Colour temperature:                          | 4000   |
| Nominal voltage:                             | 230V~, 50Hz                                  |
| Colour:                                      | white  |
| Dimensions - depth:                          | 67 mm  |
| Dimensions - width:                          | 290 mm                                       |
| Dimensions - height:                         | 290 mm                                       |
| Colour rendering index CRI:                  | >85  |
| Detection angle:                             | 360°   |
| Material of the lampshade:                   | polycarbonate                                |
| Control of the motion sensor:                | No   |
| Type of sensor:                              | PIR  |
| Detection range:                             | 6 m  |
| Adjustable daylight sensor (LUX):            | Yes  |
| Daylight sensor adjustment range (LUX):      | <3-2000lux                                   |
| Adjustable time setting (TIME):              | Yes  |
| Lighting time adjustment range (TIME):       | min: 10 sek. ± 3 sek.; max: 3 min. ± 30 sek. |
| Adjustment of motion detection range (SENS): | No   |



























