

DIN rail power supply 12V DC 1.25A, 15W, width: 1 unit

Marka: **Orno** | Symbol: **OR-PSU-1642** | Ean: **5908254803833**




PRODUCT DESCRIPTION

Highly efficient and reliable DIN rail power supply of 15W max. load and 12V DC output voltage, which can be adjusted. It has been developed for DIN rail installation and can be used in vast number of applications, e.g. industrial applications, low voltage installations, such as CCTV or alarm systems. This power supply unit includes: overload protection, anti-surge protection and overvoltage protection. An integrated diode indicates activation of the device.

TECHNICAL DATA

General information:

Rated power:	15 W
Output voltage:	12 V DC V
Input voltage:	100-230V 50-60Hz
Degree of protection (IP):	20
Output current:	1.25 A
Max. short time current rating:	2,1A
Standby power consumption:	0.3 W
Over voltage category:	III
Installation:	α DIN rail
Dimensions - depth:	18 mm
Dimensions - width:	90 mm
Dimensions - height:	58 mm

