

## DIN rail power adaptor 24VDC, 4A, 100W, width: 4 units

Marka: Orno | Symbol: OR-PSU-1649 | Ean: 5908254803901




### PRODUCT DESCRIPTION

Highly efficient and reliable DIN rail power adaptor of 100W max. load and 24V DC output voltage, which can be adjusted. It has been developed for DIN rail installation and can be used in vast number of applications, e.g. industrial applications, low voltage installations, such as CCTV or alarm systems. This power adaptor includes: overload protection, anti-surge protection and overvoltage protection. An integrated diode indicates activation of the device.

## TECHNICAL DATA

### General information:

Rated power:	96 W
Output voltage:	24V DC V
Input voltage:	100-230V 50-60Hz
Degree of protection (IP):	20
Output current:	4 A
Max. short time current rating:	4,6A
Standby power consumption:	0.3 W
Over voltage category:	III
Installation:	α DIN rail
Dimensions - depth:	70 mm
Dimensions - width:	93 mm
Dimensions - height:	58 mm

