

## Wireless wall-switch for flush-mount junction box with radio receiver, max. load 1000W, ORNO Smart Home



Marka: ORNO Home | Symbol: OR-SH-1734 | Ean: 5908254810619



### PRODUCT DESCRIPTION

This radio-controlled wall switch has been designed to wirelessly switch ON and OFF the electric circuit. It is suitable for installation in flush-mount junction boxes. The device is compatible with ORNO Smart Home based on TUYA engine, which supports Google and Alexa smart home solutions. This system is compatible with ORNO wireless sockets and remote-control units: standard models (OR-GB-417 -420), MINI models (OR-GB-438 -440) and IP44 standard socket: OR-GB-429 and MINI OR-GB-441. In order to remotely operate the switch, a remote-control unit (OR-SH-1752) or surface-mounted switch (OR-SH-1750, OR-SH-1751) from ORNO

Smart Home is required. It is possible to control the paired equipment via iPhone, iPad or other Android / iOS operated devices if you use ORNO Smart Home main control socket (OR-SH-1731).

## TECHNICAL DATA

### General information:

Type:	flush-mounted switch
Power supply of the receiver:	230V AC
Max. power of the transmitter:	< 10mW
Wi-Fi communication:	No
Type of transmission:	wireless
Max. load:	1000 W
Compliant with Orno Smart Home:	Yes
Colour:	white
Possibility of extension:	Yes
Max. current:	4.3
Installation:	flush mounting
Range in the open area:	30 m
Dimensions - depth:	25 mm
Dimensions - width:	52 mm
Dimensions - height:	52 mm
Dimensions of the mounting hole:	60 mm



