

## MINI wireless sockets with remote control, Schuko, 2+1, 2300W

Marka: **Virone** | Symbol: **RS-9(GS)** | Ean: **5908254846038**

**ViRONE**


### PRODUCT DESCRIPTION

The set of wireless mini sockets with remote control is a solution for those who want to remotely control devices both in the home and in the workplace.

The set enables to wirelessly switch on and off the indoor lighting, e. g. Christmas trees, lamps or garlands. It controls up to 8 devices. The white classic finish perfectly composes with different arrangements.

The set includes compact in size remote control (110x37x10mm), which ensures convenient one-way operation, and the two single Schuko-type sockets (2P+E) are compatible with many devices. IP20 rate facilitates indoor installation in dry places, not exposed to moisture. The max. load is 2300W. The dimensions of the socket measure 49x74x49mm each.

The remote control and the receiver are very compact in size which makes them look aesthetic. The transmitter's supply voltage (1xCR2032) and the range up to 40 m in the open field ensure stable operation in different conditions.

## TECHNICAL DATA

### General information:

Pre-programmed:	Tak
Wireless:	Tak
Signal transmission:	Sterowanie radiowe
Signal frequency [Mhz]:	433.92
Frequency [Hz]:	50
With display:	Nie
Adaptive (self-learning):	Nie
Height [mm]:	37
Width [mm]:	110
Depth [mm]:	10
Max Load [W]:	2300
Socket type:	2P+Z
Transmitter supply voltage:	1 x CR2032
Standby power consumption:	<5µA
Level of security:	IP20
Socket standard:	Schuko (typ F)
Number of wireless sockets:	2
USB charger:	Nie
Supply voltage [V]:	230

Current [A]:	10
Color:	biały
Shutters for current paths:	Tak
Possibility of expansion:	Nie
Range in open area [m]:	40
Working temperatures [°C]:	(0 – +35)
Size:	Mini
Receiver dimensions - width [mm]:	49
Receiver dimensions - height [mm]:	71
Receiver dimensions - depth [mm]:	49