

## Battery smoke detector, 9V DC, BSI

Marka: **Virone** | Symbol: **SD-1** | Ean: **5901752480896**

**ViRONE**

### PRODUCT DESCRIPTION

A battery-operated smoke alarm, a device that detects smoke particles in a closed room and alerts us to the danger at an early stage of a possible fire. The photoelectric smoke detector will work well as an additional means of monitoring the danger and thus protecting you wherever there is a risk of fire.

The device is small and lightweight, so it is recommended for self-assembly and operation. Powered by the 6LR61/ 9V battery included in the set, the device signals danger - the alarm volume is 85dB, but it will also tell

us when to replace a depleting battery. In addition, it also features an LED to visually signal the alarm.

The sensors of the detector have a lifespan of up to 10 years and the entire device complies with the European standard 14604:2005/AC1:2008, which has been certified by BSI-KM514007. The battery-operated smoke detector also has a TEST option to check the correct operation of the device.

The magnetic mounting plate (OR-DC-622), which fits many models of carbon monoxide, smoke or gas detectors, is ideal for convenient placement in the room. It enables quick and easy self-mounting of the detector without the need to drill holes in the wall. It will also work well in caravans, boats or on concrete walls or ceilings.

## TECHNICAL DATA

### General information:

Operating principle:	Optyczny
Supply voltage [V]:	9
Voltage type of supply voltage:	DC
With backup battery:	tak
Backup battery included:	Inne
Loudness [dB(A)]:	85
Mounting method:	Montaż powierzchniowy
Self-adhesive:	nie
Height [mm]:	35
Diameter [mm]:	107
Colour:	Biały
Smoke switcher:	tak
With orientation lighting:	nie
Type of test-/pause button:	Kombinowany
Degree of protection [IP]:	IP20
Standalone:	tak
Current supply primary:	Bateria/akumulator
Compliance with standards::	EN 14604:2005/AC1:2008



